

| Cat. No.   | Inputs/Outputs                                 | Range                                           | Resolution                  | Backplane Current             | Power Supply Distance Rating |
|------------|------------------------------------------------|-------------------------------------------------|-----------------------------|-------------------------------|------------------------------|
| 1769-OF4VI | 4 outputs, differential, individually isolated | $\pm 10\text{V}$<br>0...10V<br>0...5V<br>1...5V | 15 bits plus sign (bipolar) | 145 mA @ 5.1V<br>75 mA @ 24V  | 8                            |
| 1769-OF8C  | 8 outputs, single-ended                        | 0...20 mA<br>4...20 mA                          | 16 bits (unipolar)          | 140 mA @ 5.1V<br>145 mA @ 24V | 8                            |
| 1769-OF8V  | 8 outputs, single-ended                        | $\pm 10\text{V}$<br>0...10V<br>0...5V<br>1...5V | 16 bits plus sign (bipolar) | 145 mA @ 5.1V<br>125 mA @ 24V | 8                            |

## 1769 Analog RTD and Thermocouple Modules

| Cat. No. | Inputs/Outputs        | Sensors Supported                                                                                                                                                                                                                                              | Backplane Current            | Power Supply Distance Rating |
|----------|-----------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------------------------------|------------------------------|
| 1769-IR6 | 6 RTD inputs          | 100, 200, 500, 1000 $\Omega$ Platinum 385<br>100, 200, 500, 1000 $\Omega$ Platinum 3916<br>120 $\Omega$ Nickel 618<br>120 $\Omega$ Nickel 672<br>10 $\Omega$ Nickel-iron 518<br>0...150 $\Omega$<br>0...500 $\Omega$<br>0...1000 $\Omega$<br>0...3000 $\Omega$ | 100 mA @ 5.1V<br>45 mA @ 24V | 8                            |
| 1769-IT6 | 6 thermocouple inputs | Thermocouple types B, C, E, J, K, N, R, S, T<br>$\pm 50\text{V}$<br>$\pm 100\text{V}$                                                                                                                                                                          | 100 mA @ 5.1V<br>45 mA @ 24V | 8 <sup>(1)</sup>             |

(1) To reduce the effects of electrical noise, install the 1769-IT6 module at least two slots away from the AC power supplies.

## 1769 Communication and Specialty Modules

| Cat. No.     | Description                                                                                                                                                                                                                                                                                                                                                                                                                                  | Backplane Current | Power Supply Distance Rating |
|--------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|------------------------------|
| 1769-AENTR   | The adapter connects 1769 I/O modules to a linear or DLR network and uses two copper network ports to connect to the network.                                                                                                                                                                                                                                                                                                                | 500 mA @ 5V       | 5                            |
| 1769-ARM     | Use a 1769-ARM address reserve module to reserve module slots. After creating an I/O configuration and user program, you can remove and replace any I/O module in the system with a 1769-ARM module once you inhibit the removed module in the Logix Designer application.                                                                                                                                                                   | 60 mA @ 5.1V      | 8                            |
| 1769-ASCII   | The 1769-ASCII module, a general purpose two-channel ASCII interface, provides a flexible network interface to a wide variety of RS-232, RS-485, and RS-422 ASCII devices. The module provides the communication connections to the ASCII device.                                                                                                                                                                                            | 425 mA @ 5.1V     | 4                            |
| 1769-BOOLEAN | Use the 1769-BOOLEAN module in applications that require repeatability, such as material handling and packaging, when there is a requirement to activate an output based on an input's transition. If the Boolean expression is true, the output is directed to the ON state. If the Boolean expression is false, the output channel is directed to the OFF state. There are four operators that you can configure as OR, AND, XOR, or none. | 220 mA @ 5.1V     | 8                            |