

Voltage Control Accessories

For use on Bulletins 500, 500F, 500L, 500LP, 502, 502L, 503, 503L, 505, 505V, 506, 506X, 507, 507X, 509, 512, 512H, 512M, 512V, 513, 513H, 513M, 513V, 520, 520V, 522, 523, 530, 532, 533, 540, 542, 543, 570, 572, 573, 1242, 1243, 1272, 1273, 1282, 1283, 1232X, 1232V, 1233X, and 1233V; **excluding Modular Kits**

Control Circuit Transformer with Top-Mounted Fuse Block Kits (pre-wired)*❄

	NEMA Size	Primary Voltage	Capacity – 120V Secondary Voltage									
			Standard		100 W Extra		200 W Extra		300 W Extra		400 W Extra	
			VA	Cat. No.	VA	Cat. No.	VA	Cat. No.	VA	Cat. No.	VA	Cat. No.
	0...2	208V	80	1497-N1PK	130	1497-N15PK	250	1497-N7PK	350	1497-N10PK	500	1497-N18PK
		240V & 480V		1497-N2PK		1497-N16PK		1497-N8PK		1497-N11PK		1497-N19PK
		600V		1497-N3PK		1497-N17PK		1497-N9PK		1497-N12PK		1497-N20PK
	3	208V	200	1497-N4PK	250	1497-N7PK	350	1497-N10PK	500	1497-N18PK	500	1497-N18PK
		240V & 480V		1497-N5PK		1497-N8PK		1497-N11PK		1497-N19PK		1497-N19PK
		600V		1497-N6PK		1497-N9PK		1497-N12PK		1497-N20PK		1497-N20PK
	4	208V	250	1497-N7PK	350	1497-N10PK	500	1497-N18PK	—	—	—	—
		240V & 480V		1497-N8PK		1497-N11PK		1497-N19PK		—		—
		600V		1497-N9PK		1497-N12PK		1497-N20PK		—		—
	5	208V	350	1497-N10PK	500	1497-N18PK	—	—	—	—	—	—
		240V & 480V		1497-N11PK		1497-N19PK		—		—		—
		600V		1497-N12PK		1497-N20PK		—		—		—
	6	208V	500	1497-N18PK	—	—	—	—	—	—	—	—
		240V & 480V		1497-N19PK		—		—		—		—
		600V		1497-N20PK		—		—		—		—

* Transformers for NEMA sizes 7...9 are included as standard.

❄ Type 4/4X non-metallic enclosures and Type 7 & 9 hazardous location enclosures require transformers with separately mounted fuse blocks. For a complete listing of transformers, see page 8-39.

Control Circuit Transformers with Top Mounted Fuse Blocks†❄

	NEMA Size	Primary Voltage/ 3 Pole Fuse Block	Capacity – 120V Secondary Voltage	
			Standard	
			VA	Cat. No.
	0...2	208V	80	1497-B-HXDX-3-N
		240V & 480V		1497-B-BASX-3-N
		600V		1497-B-CXSX-3-N
	3	208V	200	1497-D-HXDX-3-N
		240V & 480V		1497-D-BASX-3-N
		600V		1497-D-CXSX-3-N
	4	208V	250	1497-E-HXDX-3-N
		240V & 480V		1497-E-BASX-3-N
		600V		1497-E-CXSX-3-N
	5	208V	350	1497-F-HXDX-3-N
		240V & 480V		1497-F-BASX-3-N
		600V		1497-F-CXSX-3-N

† Transformers can be installed in Type 1, 3R, 3R/4/12 painted enclosures and Type 4/4X stainless steel enclosures.

❄ Type 4/4X non-metallic enclosures and Type 7 & 9 hazardous location enclosures require transformers with separately mounted fuse blocks. For a complete listing of transformers, see page 8-39.

