

Bulletin 1492-GH, 1492-GS

High Density Supplementary Protectors

Product Selection

Using selection table on this page select Bulletin 1492-GH/GS that allows full load current nearest without exceeding application current. Also, check that inrush current is less than trip range of 6...10 I_n .

1492-GH/GS

To select a miniature circuit breaker, use the following procedure:

1. Determine the inrush correction factor from the following table.

Inrush Ratio Correction Table					
Inrush Ratio	1:1 to 1:4	1:5	1:6	1:7	1:8
Factor	1.3	1.4	1.5	1.6	1.7

Note: For resistive loads use inrush correction factor of 1.0.

2. Determine the temperature correction factor from the following table.

Ambient Temperature Correction Table							
Ambient Temperature	70 °F (21.1 °C)	100 °F (37.8 °C)	120 °F (48.9 °C)	140 °F (60 °C)	160 °F (71.1 °C)	180 °F (82.2 °C)	200 °F (93.3 °C)
Factor	1.0	1.1	1.2	1.3	1.4	1.5	1.6

3. Determine the sealed current of the load being protected.

4. Multiply the sealed current by the two correction factors and select the closest higher ampere rating.

Example — For a solenoid with sealed current of 0.5 A, an inrush ratio of 1:8, and an ambient temperature of +110 °F (43.7 °C), ($0.5 \times 1.7 \times 1.15 = 0.9775$), select the 1.0 A miniature circuit breaker. Tripping time of the miniature circuit breaker is determined from the table below. Divide the miniature circuit breaker value by the temperature correction factor from the Ambient Temperature Correction Table above to determine the actual rated current referenced in the table below.

Tripping Times in Seconds at 70 °F (21.1 °C)								
Percent Rated Current	100%	200%	300%	400%	500%	600%	1000%	2000% Greater
Tripping Times (Seconds)	No Trip	10...40	3...18	1.5...9	0.8...6	0.003...4	0.009...2	Max. 0.02

Note: When several breakers are rail mounted adjacent to each other, the no-trip current will be 80% of rated current at 70 °F (21.1 °C).

Amperage [A]	1492-GH	1492-GS		
	1-Pole	1-Pole	2-Pole	3-Pole
	Cat. No.	Cat. No.	Cat. No.	Cat. No.
0.2	1492-GH002	1492-GS1G002	1492-GS2G002	1492-GS3G002
0.5	1492-GH005	1492-GS1G005	1492-GS2G005	1492-GS3G005
0.8	1492-GH008	1492-GS1G008	1492-GS2G008	1492-GS3G008
1.0	1492-GH010	1492-GS1G010	1492-GS2G010	1492-GS3G010
1.2	1492-GH012	1492-GS1G012	1492-GS2G012	1492-GS3G012
1.5	1492-GH015	1492-GS1G015	1492-GS2G015	1492-GS3G015
2.0	1492-GH020	1492-GS1G020	1492-GS2G020	1492-GS3G020
2.5	1492-GH025	1492-GS1G025	1492-GS2G025	1492-GS3G025
3.0	1492-GH030	1492-GS1G030	1492-GS2G030	1492-GS3G030
4.0	1492-GH040	1492-GS1G040	1492-GS2G040	1492-GS3G040
5.0	1492-GH050	1492-GS1G050	1492-GS2G050	1492-GS3G050
6.0	—	1492-GS1G060	1492-GS2G060	1492-GS3G060
7.0	1492-GH070	1492-GS1G070	1492-GS2G070	1492-GS3G070
8.0	—	1492-GS1G080	1492-GS2G080	1492-GS3G080
10.0	1492-GH100	1492-GS1G100	1492-GS2G100	1492-GS3G100
12.0	—	1492-GS1G120	1492-GS2G120	1492-GS3G120
15.0	1492-GH150	1492-GS1G150	1492-GS2G150	1492-GS3G150
16.0	—	1492-GS1G160	1492-GS2G160	1492-GS3G160
20.0	—	1492-GS1G200	1492-GS2G200	1492-GS3G200
25.0	—	1492-GS1G250	1492-GS2G250	1492-GS3G250
Adding Auxiliary Contact	—	Add suffix — H1 for N.O. aux. One aux. may be installed in all devices.		
Pieces Per Carton	1			