

# ControlLogix 1756 Isolated Analog I/O Modules



Enhanced I/O for Advanced Control Applications

## Features and Benefits of the ControlLogix® 1756 Isolated Analog I/O Modules:

- Provides increased accuracy, repeatability and stability over the entire temperature operating range for enhanced precision
- Up to 24 bits of usable resolution for increased precision
- 1 ms of input sampling of floating point values for faster output response times helping to enable higher performance
- Offers industry standard 8-point channel density enabling the ability to wire more devices per module for hardware simplification
- No field calibration required for simplified device replacement and faster installation
- Synchronized input sampling for increased visibility across the system for real-time control over the EtherNet/IP network
- Per channel status and fault status indicator annunciation for more simplified troubleshooting and maintenance
- SIL 1 Systematic Capability 2 Type certified for use in a ControlLogix SIL 2 architecture
- Emulation mode helps enable customers to more seamlessly migrate from 6-channel applications

*Increased performance  
and enhanced precision*



## Enhanced Analog I/O Modules

Three 8-channel isolated designs and 12-channel and 16-channel non-isolated designs with improved functionality of analog I/O provide faster performance, more accuracy, better resolution and cost savings due to less space needed in the chassis for additional modules and power supplies.

### • 1756-IF8I General Purpose Isolated Analog Input Module

This general purpose isolated analog input module provides faster performance, accuracy and per channel configuration for voltage, current or 2-wire transmitter current sourcing.

### • 1756-IRT8I Combined Temperature Sensing Input Module

This combined temperature sensing input (Thermocouple and RTD) module provides faster performance, accuracy and per channel configuration for either RTD or Thermocouple.

### • 1756-OF8I General Purpose Current Voltage Analog Output Module

This general purpose current/voltage analog output module provides faster performance, accuracy and per channel configuration for either current or voltage.

### • 1756-IR12 non-Isolated High Density RTD module

### • 1756-IT16 non-Isolated High Density Temperature module

### • 1756-CJC Cold Junction Compensation kit for use with either 1756-IRT8I or 1756-IT16 module. Kit includes two jumpers

LISTEN.  
THINK.  
SOLVE.

## Analog 8-Channel Wiring System

The wiring system solution for the 1756 8-channel analog I/O modules enables the wiring of more devices. The 6-channel wiring system also functions with the 8-point I/O modules, allowing the preservation of existing field terminations.

- Significantly decreases wiring time from the controller card to the terminal blocks
- Provides additional capabilities for connections to the controller card via fusing and relays
- Provides a more standard connection terminal block

### The specifications for the 1756-IF8I, 1756-IRT8I, 1756-OF8I, 1756-IR12 and 1756-IT16 include:

Attribute	1756-IF8I – Input	1756-IRT8I – Input	1756-OF8I – Output	1756-IR12 – Input	1756-IT16 – Input
Inputs/ Outputs	8 isolated channels - Any combination of Voltage or Current mode	8 isolated channels- Any combination of RTD or Thermocouple mode.  Two CJC sensors for Thermocouple use. The CJC sensors, product catalog number 1756-CJC, do not come with the module. You must order the sensors separately.	8 isolated channels - Any combination of Voltage or Current mode	12 RTD non-isolated inputs	16 Thermocouple/mV inputs  Two CJC sensors for Thermocouple use. The CJC sensors, product catalog number 1756-CJC, do not come with the module. You must order the sensors separately.
Input/Output Ranges	Input ranges -10...10V 0...10V 0...5V 0...20 mA	1...500 Ω 2...1000 Ω 4...2000 Ω 8...4000 Ω -100...100 mV	-10...10V 0...10V 0...5V 0...20 mA	1...500 Ω 2...1000 Ω 4...2000 Ω 8...4000 Ω	-100...100mV
Resolution	24-bit ±10.5V (1.49 µV/count) 0...10.5V (1.49 µV/count) 0...5.25V (1.49 µV/count) 0...21 mA (2.99 nA/count)	24-bit 0...510 0: 0.06 mΩ/count 0...1020 0: 0.12 mΩ/count 0...2040 0: 0.25 mΩ/count 0...4080 0: 0.50 mΩ/count -101...101 mV: 0.0111V/count	24-bit ±10.5V (0.32 mV/count) 0...10.5V (0.16 mV/count) 0...5.25V (0.08 mV/count) 0...21 mA (0.32 µA/count)	24-bit 0...510 0: 0.06 mΩ/count 0...1020 0: 0.12 mΩ/count 0...2040 0: 0.25 mΩ/count 0...4080 0: 0.50 mΩ/count	24-bit -101...101 mV: 0.0111V/count
Current draw @ 5.1V	200 mA	200 mA	200 mA	200 mA	200 mA
Current draw @ 24V	Voltage/Non-sourcing Current mode: 150 mA  Sourcing Current mode: 400 mA  In Sourcing Current mode, the channel provides loop power	150 mA	Voltage/Current mode with 250 Ω loads: 220 mA  Current mode with 500 Ω loads: 275 mA  Current mode with 750 Ω loads: 340 mA  Current mode with 1000 Ω loads: 385 mA	70 mA	80 mA
Total Backplane Power	Voltage/Non-sourcing Current mode: 4.6 W  Sourcing Current mode: 10.6 W	4.6 W	Voltage mode: 6.3 W  Current mode with 250 Ω loads: 6.3 W  Current mode with 500 Ω loads: 7.6 W  Current mode with 750 Ω loads: 9.2 W  Current mode with 1000 Ω loads: 10.2 W	2.7W	2.9W
Thermocouple Types	N/A	8,C,D,E,J,K,N,R,S,T, TXK /XK (L)	N/A	N/A	8,C,D,E,J,K,N,R,S,T, TXK /XK (L)

Allen-Bradley, ControlLogix, LISTEN. THINK. SOLVE. and Rockwell Software are trademarks of Rockwell Automation, Inc. Trademarks not belonging to Rockwell Automation are property of their respective companies.

**www.rockwellautomation.com**

#### Power, Control and Information Solutions Headquarters

Americas: Rockwell Automation, 1201 South Second Street, Milwaukee, WI 53204-2496 USA, Tel: (1) 414.382.2000, Fax: (1) 414.382.4444

Europe/Middle East/Africa: Rockwell Automation NV, Pegasus Park, De Kleetlaan 12a, 1831 Diegem, Belgium, Tel: (32) 2 663 0600, Fax: (32) 2 663 0640

Asia Pacific: Rockwell Automation, Level 14, Core F, Cyberport 3, 100 Cyberport Road, Hong Kong, Tel: (852) 2887 4788, Fax: (852) 2508 1846