







Auxiliary Contact Blocks with Standard Auxiliary Contacts (Continued)

	Description			Connection Diagrams	For Use With NEMA Size	Cat. No.
		N.O.	N.C.			
	Auxiliary Contact Blocks for Front Mounting 4-pole - Quick and easy mounting without tools - Screw connection terminals - Switching down to 12V, 3 mA - Mirror contact performance to the main contactor poles	2	2		00...3	100-EFA22
		3	1			100-EFA31
		4	0			100-EFA40
		1	3			100-EFA13
		0	4			100-EFA04
	Auxiliary Contact Blocks for Front Mounting with A1/A2 Coil Terminal Blocks 2-pole - Quick and easy mounting without tools - Screw connection terminals - Switching down to 12V, 3mA - Mirror contact performance to the main contactor poles	1	1		00...0	100-EFC11T
		1	1		1...2 (3-pole) 00...2 (4-pole)	100-EFB11T
	Auxiliary Contact Blocks for Side Mounting 2-pole - Two-way numbering for right or left mounting on the contactor - With or without sequence terminal designations - Quick and easy mounting without tools - Screw connecting terminals - Switching down to 12V, 3mA - Mirror contact performance to the main contactor poles	1	1		1...3	100-ESB11
		1	1		00...3	100-ESA11
	Auxiliary Contact Blocks for Front Mounting for Severe Industrial Applications 1-pole - Available in two IP degrees of ingress protection - B, B2 with built-in microswitch, IP40 degree of protection – (IP20 terminals) - B3, B4 with built-in microswitch, IP67 degree of protection – (IP20 terminals), 250V, 2 A max. - Available in two voltage and current ratings - B, B3: 125V, 0.1 A max., 3V, 1 mA min. - B2, B4: 250V, 2 A max., 17V, 1 mA min.	1	0		00...3	100-ESA10B
		0	1			100-ESA01B
		1	0			100-ESA10B2
		0	1			100-ESA01B2
		1	0			100-ESA10B3
		0	1			100-ESA01B3
		1	0			100-ESA10B4
	Auxiliary Contact Blocks for Side Mounting with Sequence Terminal Designations 2-pole - Two-way numbering for right or left mounting on the contactor - Quick and easy mounting without tools - Mirror contact performance to the main contactor poles - Low power switching down to 24V 50 mA	1	1		4...5 left or right inside mounting	100-ES1-11
		1	1		4...5 left or right outside mounting	100-ES2-11