

# Ratings

Spectra™ RMS Branch Circuit Breakers without Micro EntelliGuard Trip (MET) Units

| CIRCUIT<br>BREAKER<br>CAT NO. | MAX.<br>RATING<br>AMPS | REQ.<br>BUS<br>SPACE* | CIRCUIT<br>BREAKER TYPE | SHORT CIRCUIT<br>RATINGS, KA |       |      |
|-------------------------------|------------------------|-----------------------|-------------------------|------------------------------|-------|------|
|                               |                        |                       |                         | 240V                         | 480V  | 600V |
| EZSKLA36AT1200                | 1200                   | 6X                    | SKL, 1200A, 3P, 600VAC  | 100KA                        | 65KA  | 42KA |
| EZSKHA36AT1200                | 1200                   | 6X                    | SKH, 1200A, 3P, 600VAC  | 65KA                         | 50KA  | 25KA |
| EZSKLA36AT0800                | 800                    | 6X                    | SKL, 800A, 3P, 600VAC   | 100KA                        | 65KA  | 42KA |
| EZSKHA36AT0800                | 800                    | 6X                    | SKH, 800A, 3P, 600VAC   | 65KA                         | 50KA  | 25KA |
| EZSKHH36AT0800                | 800                    | 6X                    | SKH, 800A, 3P, 600VAC   | 65KA                         | 50KA  | 25KA |
| EZSKLL36AT0800                | 800                    | 6X                    | SKL, 800A, 3P, 600VAC   | 100KA                        | 65KA  | 42KA |
| EZSGPA36AT0600                | 600                    | 4X                    | SGP, 600A, 3P, 600VAC   | 200KA                        | 100KA | 65KA |
| EZSGLA36AT0600                | 600                    | 4X                    | SGL, 600A, 3P, 600VAC   | 100KA                        | 65KA  | 65KA |
| EZSGHA36AT0600                | 600                    | 4X                    | SGH, 600A, 3P, 600VAC   | 65KA                         | 35KA  | 25KA |
| EZSGPA36AT0400                | 400                    | 4X                    | SGP, 400A, 3P, 600VAC   | 200KA                        | 100KA | 65KA |
| EZSGPP36AT0400                | 400                    | 4X                    | SGP, 400A, 3P, 600VAC   | 200KA                        | 100KA | 65KA |
| EZSGLA36AT0400                | 400                    | 4X                    | SGL, 400A, 3P, 600VAC   | 100KA                        | 65KA  | 65KA |
| EZSGLL36AT0400                | 400                    | 4X                    | SGL, 400A, 3P, 600VAC   | 100KA                        | 65KA  | 65KA |
| EZSGHA36AT0400                | 400                    | 4X                    | SGH, 400A, 3P, 600VAC   | 65KA                         | 35KA  | 25KA |
| EZSGHH36AT0400                | 400                    | 4X                    | SGH, 400A, 3P, 600VAC   | 65KA                         | 35KA  | 25KA |
| EZSGDA32AT0400                | 400                    | 4X                    | SGD, 400A, 3P, 240VAC   | 65KA                         | -     | -    |
| EZSFPA36AT0250                | 250                    | 3X                    | SFP, 250A 3P, 600VAC    | 200KA                        | 100KA | 25KA |
| EZSFLA36AT0250                | 250                    | 3X                    | SFL, 250A 3P, 600VAC    | 100KA                        | 65KA  | 25KA |
| EZSFHA36AT0250                | 250                    | 3X                    | SFH, 250A 3P, 600VAC    | 65KA                         | 35KA  | 22KA |
| EZSEPA36AT0150                | 150                    | 3X                    | SEP, 150A, 3P, 600VAC   | 200KA                        | 100KA | 25KA |
| EZSELA36AT0150                | 150                    | 3X                    | SEL, 150A, 3P, 600VAC   | 100KA                        | 65KA  | 25KA |
| EZSEHA36AT0150                | 150                    | 3X                    | SEH, 150A, 3P, 600VAC   | 65KA                         | 25KA  | 18KA |
| EZSEDA36AT0150                | 150                    | 3X                    | SED, 150A, 3P, 600VAC   | 18KA                         | 18KA  | 14KA |
| EZSEPA36AT0100                | 100                    | 3X                    | SEP, 100A, 3P, 600VAC   | 200KA                        | 100KA | 25KA |
| EZSELA36AT0100                | 100                    | 3X                    | SEL, 100A, 3P, 600VAC   | 100KA                        | 65KA  | 25KA |
| EZSEHA36AT0100                | 100                    | 3X                    | SEH, 100A, 3P, 600VAC   | 65KA                         | 25KA  | 18KA |
| EZSEDA36AT0100                | 100                    | 3X                    | SED, 100A, 3P, 600VAC   | 18KA                         | 18KA  | 14KA |
| EZSEPA36AT0060                | 60                     | 3X                    | SEP, 060A, 3P, 600VAC   | 200KA                        | 100KA | 25KA |
| EZSELA36AT0060                | 60                     | 3X                    | SEL, 060A, 3P, 600VAC   | 100KA                        | 65KA  | 25KA |
| EZSEHA36AT0060                | 60                     | 3X                    | SEH, 060A, 3P, 600VAC   | 65KA                         | 25KA  | 18KA |
| EZSEDA36AT0060                | 60                     | 3X                    | SED, 060A, 3P, 600VAC   | 18KA                         | 18KA  | 14KA |

\* Circuit breaker kits described above can be installed in the panelboard in any available position, assuming adequate space.