

Safety Switches


Accessories: NEMA Type 1 and 3R Enclosures

Spec-Setter™ Safety Switches
30-600 Amperes: TH

Auxiliary Contact Kits

—Auxiliary contacts designed to open before switch blades. UL Listed for field installation.
—Product number listed is for field installed kit.

| Ampere Rating | No. of Poles | Contacts | Contact Ratings | Product Number |
|---------------------|--------------|----------|---|----------------|
| 30A | 2 3 | DPDT | 10A, 125/250Vac 0.30A, 125Vdc 0.15A, 250Vdc | THAUX21D |
| 30A | 2 3 | SPDT | 15A, 600Vac 0.50A, 125Vdc 0.25A, 250Vdc | THAUX61S |
| 60A 100A 200A | 2 3 | DPDT | 15A, 600Vac 0.50A, 125Vdc 0.25A, 250Vdc | THAUX64D |
| 400A 600A | 2 3 | DPDT | 15A, 600Vac 0.50A, 125Vdc 0.25A, 250Vdc | THAUX66D |
| 30A 60A 100A | 6 | DPDT | 15A, 600Vac 0.50A, 125Vdc 0.25A, 250Vdc | THAUX66D |
| 200A | 6 | DPDT | 15A, 600Vac 0.50A, 125Vdc 0.25A, 250Vdc | THAUX66D2 |




THAUX21D



THAUX61S



THAUX64D



THAUX66D

Contact Pilot Duty Ratings - 600 Volt Kits

| Volts | Inrush Current | | AC Break Normal Current | DC (Resistive) Break Normal Current | |
|-------|----------------|------|----------------------------|--|----------------------|
| | N.C | N.O. | | Volts | Break Normal Current |
| 115 | 30 | 15 | 15 | 125 | 0.5 |
| 230 | 30 | 15 | 25 | 0.25 | - |
| 460 | 30 | 15 | 15 | - | - |
| 575 | 15 | 15 | 2 | - | - |

Semidust-tight Door Gasket Kits

—Types TH Indoor, TG and TH Outdoor Switches.
—Product Number listed is for field mounted kit.

| Ampere Rating | Product Number |
|--------------------|----------------|
| 30A 60A 100A | THG106 |
| 200A | THG107 |
| 400A 600A | THG108 |

