



CPT Selector and Fuse Chart

Primary Voltage: 460/230/208V, 480/240V, 440/220/200V

Secondary Voltage: 115/24V, 120/25V, 110/23V

	VA Rating	Catalog Number	Output Amps 24/115	Primary Fuse (2) required (Littelfuse KLDR) (CCMR can be used as an alternate)								Secondary Fuse (1) required(Littelfuse FLM) (KLM, FLQ, FLA can be used as substitutes) Note: Voltage Listed Below are the Primary voltages that will generate the listed secondary voltages					
												460/230/208V		480/240V		440/220/200V	
				460V	230V	208V	480V	240V	440V	220V	200V	115V	24V	120V	25V	110V	23V
	50	X4050PSF1	2.08/0.44	1/2A	1A	1-1/8A	1/2A	1A	1/2A	1-1/8A	1-1/4A	6/10A	3-2/10A	6/10A	3-2/10A	3/4A	3-1/2A
	75	X4075PSF1	3.13/0.65	8/10A	1-6/10A	1-8/10A	3/4A	1-1/2A	8/10A	1-6/10A	1-8/10A	1A	5A	1A	5A	1-1/8A	5A
	100	X4100PSF1	4.17/0.87	1A	2A	2-1/4A	1A	2A	1-1/8A	2-1/4A	2-1/2A	1-4/10A	6-1/4A	1-1/4A	6-1/4A	1-1/2A	7A
	150	X4150PSF1	6.25/1.30	1-6/10A	3-2/10A	3-1/2A	1-1/2A	3A	1-6/10A	3-2/10A	3-1/2A	2A	10A	2A	10A	2-1/4A	10A
	200	X4200PSF1	8.33/1.74	2A	4A	4-1/2A	2A	4A	2-1/4A	4-1/2A	5A	2-8/10A	12A	2-1/2A	12A	2-8/10A	12A
	250	X4250PSF1	10.42/2.17	2-1/2A	5A	6A	2-1/2A	5A	2-8/10A	5-6/10A	6-1/4A	3-1/2A	15A	3-2/10A	15A	3-1/2A	15A
	300	X4300PSF1	12.50/2.61	3-2/10A	6-1/4A	7A	3A	6-1/4A	3-2/10A	6-1/4A	7-1/2A	4A	20A	4A	15A	4-1/2A	20A
	350	X4350PSF1	14.58/3.04	3-1/2A	7-1/2A	8A	3-1/2A	7A	3-1/2A	7-1/2A	8A	5A	20A	4-1/2A	20A	5A	20A
	500	X4500PSF1	20.84/4.35	5A	5A	6A	5A	5A	5-6/10A	5-6/10A	6-1/4A	7A	30A	6-1/4A	25A	7-1/2A	30A

Primary Voltage: 460/230/208V, 480/240V, 440/220/200V

Secondary Voltage: 115V, 120V, 110V

	VA Rating	Catalog Number	Output Amps 24/115	Primary Fuse (2) required (Littelfuse KLDR) (CCMR can be used as an alternate)								Secondary Fuse (1) required(Littelfuse FLM) (KLM, FLQ, FLA can be used as substitutes)			
				460V	230V	208V	480V	240V	440V	220V	200V	115V	120V	110V	
				750	X4750PS1	6.52	8A	8A	9A	7-1/2A	7-1/2A	8A	8A	9A	

Primary Voltage: 600/575/550V

Secondary Voltage: 120/115/110V

	VA Rating	Catalog Number	Output Amps	Primary Fuse			Secondary Fuse				Use With	Catalog number	Description
				(2) required (Littelfuse KLDR) (CCMR can be used as an alternate)			(1) required (Littelfuse FLM) (KLM, FLQ, FLA can be used as substitutes)						
	460V	230V	208V	120V	115V	110V							
	50	T6050PS1	0.43	4/10A	4/10A	4/10A	6/10A	6/10A	3/4A				
	75	T6075PS1	0.65	6/10A	6/10A	6/10A	1A	1A	1-1/8A				
	100	T6100PS1	0.87	8/10A	8/10A	8/10A	1-1/4A	1-1/4A	1-1/2A				
	150	T6150PS1	1.30	1-1/4A	1-1/4A	1-1/4A	2A	2A	2-1/4A				
	200	T6200PS1	1.74	1-6/10A	1-6/10A	1-8/10A	2-1/2A	2-8/10A	3A				
	250	T6250PS1	2.17	2A	2A	2-1/4A	3-2/10A	3-1/2A	3-1/2A				
	300	T6300PS1	2.61	2-1/2A	2-1/2A	2-1/2A	4A	4A	4-1/2A				
350	T6350PS1	3.04	2-8/10A	3A	3A	4-1/2A	5A	5A					
500	T6500PS1	4.35	4A	4A	4-1/2A	6-1/4A	7A	7-1/2A					
750	T6750PS1	6.52	6-1/4A	6-1/4A	6-1/4A	10A	10A	10A					

All Transformers Include Fuse Blocks

All Transformers Include Fuse Blocks