

Disconnect Switch

NEW



Switch Rating [A]	Maximum Horsepower							Switch with Right-Hand Mechanism (Non-Fusible and Fusible)
	3-Phase				1-Phase		DC	
	200...208V	230V	460V	575V	115V	230V	250V DC	
30	7.5	7.5	15	20	2	3	5	1494F-N30
60	15	15	30	50	3	10	10	1494F-N60
100	25	30	60	75	—	15	20	1494F-N100
200	50...60	60	125	150	—	—	40	1494F-N200

Fuse Clip Kit and Fuse Block Adapter Plate Kit

NEW



Select a fuse block adapter plate kit catalog number AND a fuse clip kit catalog number.



Switch Rating [A]	Fuse Clip Rating [A]	Fuse Clip Kit				
		Class R		Class J	Class H	
		250V	600V	250/600V	250V	600V
		Cat. No.	Cat. No.	Cat. No.	Cat. No.	Cat. No.
30	30	1401-N50	1401-N51	1401-N42	1401-N41	1401-N42
	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43
60	30	1401-N50	1401-N51	1401-N42	1401-N41	1401-N42
	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43
	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44
100	60	1401-N51	1401-N52	1401-N43	1401-N42	1401-N43
	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44
	200	1401-N54	1401-N54	1401-N45	1401-N45	1401-N45
200	100	1401-N53	1401-N53	1401-N44	1401-N44	1401-N44
	200	1401-N54	1401-N54	1401-N45	1401-N45	1401-N45
	400	—	—	1401-N171	—	—



(order both a fuse clip kit AND fuse block adapter plate kit)

Fuse Block Adapter Plate Kit
Cat. No.
1494F-F30
1494F-F60
1494F-F100
1494F-F200