

Bulletin 100-C/104-C
MCS-C Contactors
 Product Selection, Continued

Reversing AC Contactors



- AC Operating Mechanism, 3 Main Contacts
- Includes Mechanical/Electrical Interlock
- Includes Reversing Power Wiring



Cat. No. 104-C09®22



Cat. No. 104-C30®22



Cat. No. 104-C43®22

I _e		Ratings for Switching AC Motors										Auxiliary Contacts Installed per Contactor			
		AC-2, AC-3, AC-4													
[A]		kW (50 Hz)				HP (60 Hz)									
AC-3	AC-1	230V	380V 415V 400V	500V	690V	1Ø		3Ø						Cat. No.	*
460V	40°C		115V			230V	200V	230V	460V	575V	N.O.	N.C.			
9	25	3	4	4	4	1/3	1	2	2	5	7-1/2	1	1	104-C09®22	
12	25	4	5.5	5.5	5.5	1/2	2	3	3	7-1/2	10	1	1	104-C12®22	
16	32	5.5	7.5	7.5	7.5	1	3	5	5	10	10	1	1	104-C16®22	
23	32	7.5	11	11	10	2	3	5	7-1/2	15	15	1	1	104-C23®22	
30	45	10	15	15	15	2	5	7-1/2	10	20	20	0	1	104-C30®02	
												1	1	104-C30®22	
37	50	11	18.5	18.5	18.5	3	5	10	10	25	25	0	1	104-C37®02	
												1	1	104-C37®22	
43	63	13	22	22	22	3	7.5	10	15	30	30	0	1	104-C43®02	
												1	1	104-C43®22	
60	90	18.5	30	30	30	5	10	15	20	40	40	0	1	104-C60®02	
												1	1	104-C60®22	
72	90	22	37	37	37	5	15	20	25	50	50	0	1	104-C72®02	
												1	1	104-C72®22	
85	100	25	45	45	45	7-1/2	15	25	30	60	60	0	1	104-C85®02	
												1	1	104-C85®22	

⊗ **Voltage Suffix Code**

The Cat. No. as listed is incomplete. Select a voltage suffix code from the table below to complete the Cat. No. Example: 120V, 60 Hz: Cat. No. 104-C09®22 becomes Cat. No. 104-C09D22.

Standard Coil Voltages	12	24	32	36	42	48	100	100- 110	110	120	127	200	200- 220	208	208- 240	220- 230	230	230- 240	240	277	347	380	380- 400	400	400- 415	440	480	500	550	600
50 Hz	R	K	V	W	X	Y	KP	—	D	P	S	KG	—	—	—	F	—	VA	T	—	—	—	N	—	G	B	—	M	C	—
60 Hz	Q	J	—	V	—	X	—	KP	—	D	—	—	KG	H	L	—	—	—	A	T	I	E	—	—	—	N	B	—	—	C
50/60 Hz	—	KJ	—	—	—	KY	KP	—	KD	—	—	KG	—	—	—	—	KF	—	KA	—	—	—	—	KN	—	KB	—	—	—	—

Accessories — Page 11
 Specifications — Page 16
 Approximate Dimensions — Page 28