
# 22.5 mm Configured Pendant Stations

## **Product Selection**

### **Product Selection Enclosures**

	Pendants — Yellow
Pkg. Quantity	Plastic IP66 Cat. No.*
	800FC-3Z
4	800FC-5Z
I	800FC-7Z
	800FC-9Z
	Pkg. Quantity









Cat. No. 800FC-7Z

#### 1-, 2-, and 3-Speed Operators §\*

800FP - C  $\frac{A}{a} \frac{1}{b} \frac{U243}{c}$ 



Operator Type						
Code	Description					
Α	1-speed single arrow					
D	1-speed double arrow					
В	2-speed					
	3 speed					

\* Proper contact block assembly of these devices is required. Please see contact block information on page 104.

Cap Color					
Code Description					
1	White				
2	Black				

#### **Arrow Direction Chart**

**FORWARD RIGHT** 









10





**DOWN REVERSE** 

	Symbol								
		\/-!:-!:M-	Description‡						
	Code	Valid with Table a Selections:	Vertical I	Mounting	Horizontal Mounting				
			Black with White Arrow	White with Black Arrow	White with Black Arrow	Black with White Arrow			
	U100	A, B, C	Blank	Blank	Blank	Blank			
			One-Speed Operators						
	U241		DOWN	UP	_	_			
( 4 )	U243		_	_	RIGHT	LEFT			
	U244	A	REVERSE	FORWARD	_	_			
	U246		_	_	FORWARD	REVERSE			
	U700		LEFT	RIGHT	UP	DOWN			
	U261		DOWN FAST	UP FAST	_	_			
	U263		_	_	RIGHT FAST	LEFT FAST			
	U264	D	REVERSE FAST	FORWARD FAST	_	_			
	U266		_	_	FORWARD FAST	REVERSE FAST			
	U260		LEFT FAST	RIGHT FAST	UP FAST	DOWN FAST			
		Two-Speed Operators							
	U271	В	2-speed DOWN	2-speed UP	_	_			
	U273		_	_	2-speed RIGHT	2-speed LEFT			
	U274		2-speed REVERSE	2-speed FORWARD	_	_			
	U276		_	_	2-speed FORWARD	2-speed REVERSE			
	U270		2-speed LEFT	2-speed RIGHT	2-speed UP	2-speed DOWN			
	Three-Speed Operators								
	U291		3-speed DOWN	3-speed UP	_	_			
	U293		_	_	3-speed RIGHT	3-speed LEFT			
	U294	С	3-speed REVERSE	3-speed FORWARD					
	U296				3-speed FORWARD	3-speed REVERSE			
	U290		3-speed LEFT	3-speed RIGHT	3-speed UP	3-speed DOWN			

- Note: Please see page 104 for proper latch and contact block configurations.

  ‡ Text (DOWN, UP, LEFT, etc.) indicates arrow direction. Text is **not** printed on operators.

  § Cat. No. 800F-ALP (standard latch) and Cat. No. 800FC-ALP (mechanical interlock latch) can be
- used with these operators.
- Booted style of operators for pendant stations.