



Bulletin 100L Electrically Held Lighting Contactors

- · Electrically held
- 20 A rating
- 4-, 8-, and 12-pole configurations
- Open or enclosed
- · CSA Certified, cULus Listed

Bulletin 100L lighting contactors have been designed to control a variety of lighting loads. The product offering includes 4-, 8-, and 12pole contactors with or without enclosures. The Bulletin 100L line of lighting contactors has been designed with a 20 A rating for all popular lighting loads and other non-motor applications including tungsten filament lighting loads, electric discharge (fluorescent) loads, electric furnaces, and electric water heaters. In addition these contactors have been designed to meet the requirements of both CSA and UL.

Your order must include: cat. no. of the contactor specified with coil voltage code and, if required, cat. no. of any accessories

Table of Contents

Product Selection this page Specifications..... this page Wiring Diagram this page Approximate Dimensions...... 6-5

Standards Compliance

CSA C22.2, No. 14 UL 508 Meets the material restrictions for European Directive 2002/95/IEC-EU-RoHS

Certifications

CE Marked cULus Listed (File No. E14843; Guide NRNT, NRNT7)

Product Selection

No. of Poles∗	Cat. No.			
4	100L-C20N⊗4			
8	100L-C20N⊗8			
12	100L-C20N⊗12			
4	100L-C20A⊗4			
8	100L-C20A⊗8			
12	100L-C20A⊗12			
4	100L-C20F⊗4			
8	100L-C20F⊗8			
12	100L-C20F⊗12			
	4 8 12 4 8 12 4 8			

* These contactors do not include an auxiliary hold-in contact. If a hold-in contact is required it can be ordered by adding a suffix -90 to the cat. no. Example: Cat. No. 100L-C20NJ4-90.

Specifications Ratings

		Max. AC Volts, Poles to Load*					
Type of Load	Max. Current [A]	1 for 1Ø	3 for 3Ø				
Tungatan	20	277	480Y/277V				
Tungsten	15	347	600Y/347V				
Ballast	20	277	480Y/277V				
Dallast	15	347	600Y/347V				
General Use Resistance Heating	30	600	600				

^{\$20} A, 250V DC max. with 3 poles in series.

⊗ Coil Voltage Code

The cat. no. as listed is incomplete. To complete the cat. no., select a coil voltage code from the chart below and insert into the cat. no. Example: Cat. No. 100L-C20N&4 becomes Cat. No. 100L-C20NJ4. For other voltages, consult your local Rockwell Automation sales office or Allen-Bradley distributor.

[V]	24	48	110	120	208	220	240	277	347	380 400	415	440	480	500	600
AC, 50Hz	K	Υ	D	Р	_	Α	Т	_	_	N	G	В	_	М	_
AC, 60Hz	J	X	_	D	Н	L	Α	Т	- 1		_	N	В	_	С

Wiring Diagrams





