



Digital Interface Modules (IFMs)


Fusible

Fusible modules provide a convenient method of adding overcurrent protections into your programmable controller wiring. These modules have 5 x 20 fuse holders on-board and are available with and without blown fuse indication. The 24V, 120V, and 240V blown fuse indicators reduce the troubleshooting time to locate and replace a blown fuse on the IFM. Fusible modules have an easy-to-remove, transparent plexiglass cover that prevents objects from contacting fuse circuitry under normal operation. Removal of fuses from the standard fuse holder is aided by fuse pullers (fuses not provided). The fusible modules also have two or four terminals per I/O point to create a power bus for input and output load connections. Fusible modules are available in both isolated (Cat. No. 1492-IFM20F-FS24-2) and nonisolated (Cat. No. 1492-IFM20F-F24-2) versions. There are a select number of fusible IFMs available for input modules provided. The fusible modules also have two or four terminals per I/O point to create a power bus for input and output load connections. Fusible modules are available in both isolated (Cat. No. 1492-IFM20F-FS24-2) and nonisolated (Cat. No. 1492-IFM20F-F24-2) versions. There are a select number of fusible IFMs available for input modules.

**Fused Extra Terminals**

For 20-point: Cat. No. 1492-IFM20FS-F120-4,
1492-IFM20FS-F120A-4, 1492-IFM20FS-F240-4

For 40-point: Cat. No. 1492-IFM40FS-F24-4, 1492-IFM40FS-F24A-4,
1492-IFM40FS-F120-4, 1492-IFM40FS-F120A-4,
1492-IFM40FS-F240-4, 1492-IFM40F-FS240A-4

**Fused Extra Terminals**


For 20-point: Cat. No. 1492-IFM20F-F-2, 1492-IFM20F-F24-2,
1492-IFM20F-F24A-2, 1492-IFM20F-F120-2, 1492-IFM20F-F120A-2,
1492-IFM20F-F240-2, 1492-IFM20FS-F-2, 1492-IFM20FS-F24-2,
1492-IFM20FS-F24A-2

For 40-point: Cat. No. 1492-IFM40F-F-2, 1492-IFM40F-F24-2,
1492-IFM40F-F120-2, 1492-IFM40FS-F-2, 1492-IFM40FS-F24-2,
1492-IFM40FS-F120-2, 1492-IFM40FS-F24-4, 1492-IFM40FS-F24A-4,
1492-IFM40FS-F120-4, 1492-IFM40FS-F120A-4, 1492-IFM40FS-F240-4



40-pin cable connector Isolated Fusible module
(no fuse blown indication): Cat. No. 1492-IFM40F-FS-2

40-pin cable connector Isolated Fusible module with 24V blown fuse
indication: Cat. No. 1492-IFM40F-FS24A-2



Safety Integrity Level (SIL2)
Cat. No. 1492-TIFM40F-F24A-2

Programmable Controller Wiring Systems

Bulletin 1756 ControlLogix Modules

Digital IFMs and Cables for Bulletin 1756 ControlLogix 8-point and 16-point I/O Modules

Voltage [V]	Term. per I/O	Description	Fixed Terminal Block	Removable Terminal Block	RTB Plugs ❖	Bulletin 1756 ControlLogix I/O Module															
			Cat. No.	Cat. No.		Cat. No.	Digital Cable Cat. No. Suffix +	1756-IA8D	1756-IA16	1756-IB16	1756-IC16	1756-IN16	1756-IV16	1756-OA8	1756-OA8D	1756-OA8E	1756-OA16	1756-OB8	1756-OB16E	1756-OC8	1756-QN8
Feed-Through																					
24...	1	Standard	1492-IFM20F	1492-RIFM20F	1492-RTB10❖	U	X	X	X	X	X	U	U	U	X	U	X	U	U	X	
240	2	Extr. Term.	1492-IFM20F-2	1492-RIFM20F-2	1492-RTB20❖	U	X	X	X	X	X	U	U	U	X	U	X	U	U	X	
24...	1	Narrow	1492-IFM20FN	1492-RIFM20FN	1492-RTB20❖	U	X	X	X	X	X	U	U	U	X	U	X	U	U	X	
120	3	Sensor	1492-IFM20F-3	—	—		X	X	X	X	X										
LED Indicating																					
24	1	Standard	1492-IFM20D24	—	—			X		X	X							X			X
	1	Narrow	1492-IFM20D24N	—	—			X		X	X							X			
	2	Extr. Term. (input)	1492-IFM20D24A-2	—	—			X		X	X										
	2	Extr. Term. (output)	1492-IFM20D24-2	—	—													X			X
	3	Sensor	1492-IFM20D24-3	—	—			X		X	X										
	4	Isolated w/Extr.Term.	1492-IFM20DS24-4	—	—				X		X	X						W		W	W
120	1	Narrow	1492-IFM20D120N	—	—	U	X								X						
	2	Extr. Term. (input)	1492-IFM20D120A-2	—	—	U	X														
	2	Extr. Term. (output)	1492-IFM20D120-2	—	—										X						
	4	Isolated w/Extr.Term.	1492-IFM20DS120-4	—	—								W	V	V						
Fusible																					
24	2	Blown fuse LED	1492-IFM20F-F24-2	1492-RIFM20F-F24-2	1492-RTB20❖													X			X
	2	Blown fuse LED (input)	1492-IFM20F-F24A-2	1492-RIFM20F-F24A-2				X		X											
24... 120	2	Extra Terminals	1492-IFM20F-F-2	1492-RIFM20F-F-2										X		X				X	
120	2	Blown fuse LED	1492-IFM20F-F120-2	1492-RIFM20F-F120-2										X							
	2	Blown fuse LED (input)	1492-IFM20F-F120A-2	1492-RIFM20F-F120A-2		X															
Fusible, Isolated																					
24	2	Blown fuse LED	1492-IFM20F-FS24-2	—	—												W		W	W	
24... 120	2	Extra Terminals	1492-IFM20F-FS-2	—	—							W	V	V		W		W	W		
120	2	Blown fuse LED	1492-IFM20F-FS120-2	—	—							W	V	V							
	4	Blown fuse LED	1492-IFM20F-FS120-4	—	—							W	V	V							
	4	Blown fuse LED (input)	1492-IFM20F-FS120A-4	—	—	U															
240	4	Blown fuse LED	1492-IFM20F-FS240-4	—	—							W									

See footnotes on the following page.



Digital IFMs and Cables for Bulletin 1769 CompactLogix 8-Point and 16-Point I/O Modules

Voltage [V]	Term. per I/O	Description	Fixed Terminal Block	Removable Terminal Block	RTB Plugs ❖	Bulletin 1769 CompactLogix I/O Module															
						1769-IA8I	1769-IA16	1769-IQ16	1769-IQ16F	1769-IM12	1769-OA8	1769-OA16	1769-OB8	1769-OB16	1769-OV16	1769-OW8	1769-OW8I	1769-OW16			
			Cat. No.	Cat. No.	Cat. No.	Digital Cable Cat. No. Suffix +															
Feed-Through																					
120	1	Narrow	1492-IFM20FN	1492-RIFM20FN	1492-RTB10❖	F69	A69	B69	B69		C69	M69	L69	E69	E69	C69			M69		
120	3	Sensor	1492-IFM20F-3	—	—	—	A69	B69	B69												
240	1	Standard	1492-IFM20F	1492-RIFM20F	1492-RTB20❖	F69	A69	B69	B69	G69	C69	M69	L69	E69	E69	C69	D69		M69		
240	2	Extr. Term.	1492-IFM20F-2	1492-RIFM20F-2	1492-RTB20❖	—	A69	B69	B69	G69	C69	M69	L69	E69	E69	C69	—		M69		
LED Indicating																					
24	1	Standard	1492-IFM20D24	—	—			B69	B69						E69	E69			M69		
	1	Narrow	1492-IFM20D24N	—	—			B69	B69						E69				H69		
	2	Extr. Term. (output)	1492-IFM20D24-2	—	—										E69	E69			M69		
	2	Extr. Term. (input)	1492-IFM20D24A-2	—	—			B69	B69												
	3	Sensor	1492-IFM20D24-3	—	—			B69	B69												
	4	Isolated	1492-IFM20DS24-4	—	—													C69	D69		
120	1	Standard	1492-IFM20D120§	—	—		A69					M69							M69		
	1	Narrow	1492-IFM20D120N	—	—		A69					H69							H69		
	2	Extr. Term. (output)	1492-IFM20D120-2	—	—							M69							M69		
	2	Extr. Term. (input)	1492-IFM20D120A-2	—	—		A69														
	4	Isolated	1492-IFM20DS120-4	—	—						C69							C69	D69		
240	2	Extr. Term. (output)	1492-IFM20D240-2	—	—							M69							M69		
	2	Extr. Term. (input)	1492-IFM20D240A-2	—	—					G69											
Fusible																					
24	2	Extr. Term., blown fuse LED	1492-IFM20F-F24-2	1492-RIFM20F-F24-2	1492-RTB20❖										E69	E69			M69		
	2	Extr. Term. (input), blown fuse LED	1492-IFM20F-F24A-2	1492-RIFM20F-F24A-2	1492-RTB20❖			B69 *	B69 *							E69					
24...120	2	Extr. Term. (output)	1492-IFM20F-F-2	1492-RIFM20F-F-2	1492-RTB20❖							M69		E69	E69			M69			
120	2	Extr. Term., blown fuse LED	1492-IFM20F-F120-2	1492-RIFM20F-F120-2	1492-RTB20❖							M69							M69		
	2	Extr. Term. (input), blown fuse LED	1492-IFM20F-F120A-2	1492-RIFM20F-F120A-2	1492-RTB20❖		A69														
Fusible, Isolated																					
24	2	Extr. Term., blown fuse LED	1492-IFM20F-FS24-2	—	—													C69	D69		
24...120	2	Extr. Term. (output)	1492-IFM20F-FS-2	—	—						C69							C69	D69		
120	2	Extr. Term. (output), blown fuse LED	1492-IFM20F-FS120-2	—	—							C69						C69	D69		
	4	Extr. Term. (output), blown fuse LED	1492-IFM20F-FS120-4	—	—							C69						C69	D69		
240	4	Extr. Term. (output), blown fuse LED	1492-IFM20F-FS240-4	—	—														D69		

See footnotes on the following page.

Programmable Controller Wiring Systems

Specifications

Digital IFM Specifications

Digital IFM Cat. No.	Voltage Range	Dimensions (W x H x D) [in.]*	Indicator Circuit Current (Nominal) [mA]	Label Card Cat. No.*
1492-IFM20F, -RIFM20F	0...264V AC/DC	4.33 x 3.27 x 2.78†	—	46006-190-01, 46006-233-01
1492-IFM20FN, -RIFM20FN	0...132V AC/DC	2.36 x 3.27 x 2.78†	—	46006-197-01, -237-01, -220-01
1492-IFM20F-2, -RIFM20F-2	0...264V AC/DC	4.33 x 3.27 x 2.78†	—	46006-192-01, -235-01, -221-01
1492-IFM20F-3	0...132V AC/DC	4.33 x 3.27 x 2.78	—	46006-210-01
1492-IFM20D24	10...30V AC/DC	4.33 x 3.27 x 2.78	2	46006-190-01, 46006-233-01
1492-IFM20D24N	10...30V AC/DC	2.36 x 3.27 x 2.78	2	46006-197-01, -237-01, -220-01
1492-IFM20D24-2	10...30V AC/DC	4.33 x 3.27 x 2.78	2	46006-192-01, -235-01, -221-01
1492-IFM20D24A-2	10...30V AC/DC	4.33 x 3.27 x 2.78	2	46006-211-01
1492-IFM20DS24-4	10...60V AC/DC	4.33 x 3.27 x 2.78	1.6	46006-209-01
1492-IFM20D24-3	10...30V AC/DC	4.33 x 3.27 x 2.78	2	46006-193-01, 46006-236-01
1492-IFM20D120	85...132V AC/DC	4.33 x 3.27 x 2.78	2.5	46006-190-01, 46006-233-01
1492-IFM20D120N	85...132V AC	2.36 x 3.27 x 2.78	2.5	46006-197-01, -237-01, -220-01
1492-IFM20D120-2	85...132V AC	4.33 x 3.27 x 2.78	2.5	46006-192-01, -235-01
1492-IFM20D120A-2	85...132V AC	4.33 x 3.27 x 2.78	2.5	46006-211-01
1492-IFM20DS120-4	85...132V AC	4.33 x 3.27 x 2.78	2.6	46006-209-01
1492-IFM20D240-2	204...264V AC	4.33 x 3.27 x 2.78	2.5	46006-192-01, -235-01
1492-IFM20D240A-2	204...264V AC	4.33 x 3.27 x 2.78	2.5	46006-211-01
1492-IFM20F-F-2, -RIFM20F-F-2	0...132V AC/DC	4.33 x 3.27 x 2.78†	—	46006-192-01, -235-01, -221-01
1492-IFM20F-F24-2, -RIFM20F-F24-2	10...30V AC/DC	4.33 x 3.27 x 2.78†	2	46006-192-01, -235-01, -221-01
1492-IFM20F-F24A-2, -RIFM20F-F24A-2	10...30V AC/DC	4.33 x 3.27 x 2.78†	2.4	46006-212-01, -189-01
1492-IFM20F-F120-2, -RIFM20F-F120-2	85...132V AC	4.33 x 3.27 x 2.78†	2.5	46006-192-01, -235-01, -221-01
1492-IFM20F-F120A-2, -RIFM20F-F120A-2	85...132V AC/DC	4.33 x 3.27 x 2.78†	1.2	46006-212-01, -189-01
1492-IFM20F-F240-2	204...264V AC	4.72 x 3.27 x 2.78	1.2	46006-192-01, -235-01
1492-IFM20F-FS-2	0...132V AC/DC	2.36 x 3.27 x 2.78	—	46006-204-01
1492-IFM20F-FS24-2	10...30V AC/DC	2.36 x 3.27 x 2.78	2	46006-204-01
1492-IFM20F-FS24A-4	10...30V AC/DC	3.15 x 3.27 x 2.78	2.4	46006-215-01
1492-IFM20F-FS120-2	85...132V AC/DC	2.36 x 3.27 x 2.78	2.5	46006-204-01
1492-IFM20F-FS120-4	85...132V AC/DC	4.33 x 3.27 x 2.78	1.2	46006-214-01
1492-IFM20F-FS120A-4	85...132V AC/DC	3.15 x 3.27 x 2.78	2.2	46006-215-01
1492-IFM20F-FS240-4	204...264V AC	4.33 x 3.27 x 2.78	1.2	46006-214-01
1492-IFM40F, -RIFM40F	0...132V AC/DC	4.33 x 3.27 x 2.78†	—	46006-191-01, -234-01, -252-01
1492-IFM40F-2	0...132V AC/DC	8.27 x 3.27 x 2.78	—	46006-224-01, -225-01, -239-01, -240-01, -253-01
1492-RIFM40F-2	0...132V AC/DC	9.05 x 3.27 x 2.78	—	46006-224-01, -225-01, -239-01, -240-01, -253-01
1492-IFM40F-3	0...60V AC/DC	8.27 x 3.27 x 2.78	—	46006-193-01, 46006-236-01
1492-IFM40D24, -RIFM40D24	10...30V AC/DC	4.33 x 3.27 x 2.78†	2	46006-191-01, -234-01, -252-01
1492-IFM40D24-2	10...30V AC/DC	8.27 x 3.27 x 2.78	2	46006-194-01, -195-01, -253-01
1492-IFM40D24A-2	10...30V AC/DC	8.27 x 3.27 x 2.78	2	46006-224-01, -225-01, -239-01, -240-01, -253-01
1492-RIFM40D24A-2	10...30V AC/DC	9.05 x 3.27 x 2.78	2	46006-224-01, -225-01, -239-01, -240-01, -253-01
1492-IFM40DS24-4	10...60V AC/DC	6.69 x 3.27 x 2.78	4.1	46006-208-01
1492-IFM40DS24A-4	10...30V AC/DC	6.69 x 3.27 x 2.78	4.1	46006-208-01
1492-IFM40D24-3	10...30V AC/DC	8.27 x 3.27 x 2.78	2	46006-193-01, 46006-236-01
1492-IFM40D120-2	85...132V AC	8.27 x 3.27 x 2.78	2.5	46006-194-01, -195-01, -253-01
1492-IFM40D120A-2	85...132V AC	8.27 x 3.27 x 2.78	2.5	46006-194-01, -195-01, 253-01
1492-IFM40DS120-4	85...132V AC	6.69 x 3.27 x 2.78	2.6	46006-208-01
1492-IFM40DS120A-4	85...132V AC	6.69 x 3.27 x 2.78	2.6	46006-208-01
1492-IFM40DS240A-4	204...264V AC	6.69 x 3.27 x 2.78	2.6	46006-208-01
1492-IFM40F-F-2	0...132V AC/DC	8.27 x 3.27 x 2.78	—	46006-194-01, -195-01, -253-01
1492-IFM40F-F24-2	10...30V AC/DC	8.27 x 3.27 x 2.78	2	46006-224-01, -225-01, -239-01, -240-01, 253-01
1492-RIFM40F-F24-2	10...30V AC/DC	8.66 x 3.27 x 2.78	2	46006-224-01, -225-01, -239-01, -240-01, 253-01
1492-IFM40F-F24D-2	10...30V AC/DC	4.72 x 3.27 x 2.78	<0.05	46006-201-01
1492-IFM40F-F24AD-4	10...30V AC/DC	7.09 x 3.27 x 2.78	<0.05	46006-206-01
1492-IFM40F-F120-2	85...132V AC	8.27 x 3.27 x 2.78	2.5	46006-194-001, -195-01, -253-01
1492-IFM40F-FS-2	0...132V AC/DC	4.72 x 3.27 x 2.78	—	46006-201-01
1492-IFM40F-FS-4	0...264V AC/DC	7.09 x 3.27 x 2.78	—	46006-207-01
1492-IFM40F-FS24-2	10...30V AC/DC	4.72 x 3.27 x 2.78	2	46006-201-01
1492-IFM40F-FS24-4	10...30V AC/DC	7.09 x 3.27 x 2.78	2.4	46006-207-01
1492-IFM40F-FS120-2, -RIFM40F-FS120-2	85...132V AC/DC	4.72 x 3.27 x 2.78†	2.5	46006-201-01
1492-IFM40F-FS120-4	85...132V AC/DC	7.09 x 3.27 x 2.78	1.4	46006-206-01
1492-RIFM40F-FS120-4	85...132V AC/DC	7.87 x 3.27 x 2.78	1.4	46006-226-01
1492-IFM40F-FS240-4	204...264V AC/DC	7.09 x 3.27 x 2.78	2.4	46006-207-01
1492-IFM40F-FS24A-4	10...30V AC/DC	7.09 x 3.27 x 2.78	3.1	46006-226-01
1492-IFM40F-FS120A-4	85...132V AC/DC	7.09 x 3.27 x 2.78	1.4	46006-226-01
1492-RIFM40F-FS120A-4	85...132V AC/DC	7.87 x 3.27 x 2.78	1.4	46006-226-01
1492-IFM40F-FSA-4	85...132V AC/DC	7.09 x 3.27 x 2.78	—	46006-226-01
1492-IFM40F-FS240A-4	85...264V AC/DC	7.09 x 3.27 x 2.78	1.4	46006-226-01
1492-TIFM40F-F24-2	24V DC	8.66 x 3.27 x 2.74	—	46006-230-01
1492-TIFM40F-F24A-2	24V DC	9.5 x 3.27 x 2.74	3	46006-230-01

* To convert to millimeters, multiply inches by 25.4

* Ships with each module. For spare part, precede the part number with the letter "W."

† Add 0.39 in. to the width dimension for Bulletin 1492-Rxxx modules.

www.ab.com/catalogs Preferred availability cat. nos. are bold.

Publication A117-CA001A-EN-P


Allen-Bradley