

Color	Handles (Includes Legend Plate and Control Knob)			
Red/Yellow (Emergency Stop colors)				Bulletin 194L handles are available in both screw fixing and 22.5 mm mounting hole style. IP66, UL Type 3/3R/12 for all 194L Handles
	Type I	Type L With Locking For One Padlock (Padlock Not Included)	Type N ★	
Black/Grey (Standard Operation colors)				
	Type A	Type E With Locking For One Padlock (Padlock Not Included)	Type G★	Type S

★ These handles are for use with -175 and -178 (ON-OFF) switches only and are dual marked with ON-OFF and 1-0.

Catalog Number Explanation

194L – HE 6 N – 175
a b c d

a	
Code	Installation Type
HC	22.5 mm mounting hole style handle (for use with front-mounted switches)
HE	Screw-mounting handle (for use with front- and base-mounted switches)

b			
Code	Use with Handle Type	Handle Legend Plate Size	Use With 194L Switch Size
4	A, E, I, L	48 mm x 48 mm (1-57/64 in. x 1-57/64 in.)	194L-A12...A25 194L-E12...E25 194L-C32...C40
	S	48 mm x 62 mm (1-57/64 in. x 2-7/16 in.)	
6	A, E, I, L	64 mm x 64 mm (2-33/64 in. x 2-33/64 in.)	194L-A12...40 A 194L-E12...40 A
	G, N‡	67 mm x 67 mm (2-41/64 in. x 2-41/64 in.)	
	S	64 mm x 78 mm (2-33/64 in. x 3-5/64 in.)	

‡ Use Type G and N with ON-OFF function only (selection "d").

c		
Code	Legend Plate Type	Color
A	Square	Grey/black
I	Square	Red/yellow
E	Square/lockable	Grey/black
L	Square/lockable	Red/yellow
G	Disc/lockable (up to 3 locks)	Grey/black
N	Disc/lockable (up to 3 locks)	Red/yellow
S	Large square with extra legend area	Grey/black

d
See Table on the next page.

d								
Code	Description	Legend Marking	Code	Description	Legend Marking	Code	Description	Legend Marking
150	O-I		426	1-2-3-4 (45° step switch)		551	0-1-2-3 (60° step switch)	
150I	OFF-ON		427	1-2-3-4-5 (45° step switch)		552	0-1-2-3-4 (60° step switch)	
175	O-I		428	1-2-3-4-5-6 (45° step switch)		553	0-1-2-3-4-5 (60° step switch)	
175I	OFF-ON		450	1-2-3 (60° step switch)		725	0-Y-Δ (45° / 90° Star-Delta switch)	
178	O-I		451	1-2-3-4 (60° step switch)		732	0-Y-Δ (45° / 90° Star-Delta switch)	
178I	OFF-ON		452	1-2-3-4-5 (60° step switch)		750	0-Y-Δ (60° Star-Delta switch)	
225	1-2 (45° Changeover without O)		453	1-2-3-4-5-6 (60° step switch)		754	Same as Code 350. Use order code 350.	
250	1-2 (60° Changeover without O)		500	0-1-2-3-4 (30° step switch)		825	0-RN-SN-TN-TR-ST-RS (45° voltmeter switch)	
300	1-0-2 (30° Changeover with spring return)		501	0-1-2-3-4-5 (30° step switch)		827	0-RS-ST-TR (45° voltmeter switch)	
325	1-0-2 (45° Changeover with O)		525	0-1-2 (45° step switch)		875	0-1-2-3 (90° ammeter switch — 3 c.t.'s)	
326	Same as Code 325. Use order code 325.		526	0-1-2-3 (45° step switch)		876	1-2-3-4 (90° ammeter switch — 4 c.t.'s)	
350	1-0-2 (Reversing 60° Changeover with O)		527	0-1-2-3-4 (45° step switch)		877	0-1 (90° ammeter switch — 1 c.t.)	
375	1-0-2 (90° Changeover with O)		528	0-1-2-3-4-5 (45° step switch)		—	—	—
425	1-2-3 (45° Step Switch)		550	0-1-2 (60° step switch)		—	—	—

Frequently Ordered 194L Handles — Base/Front-Mounted Switch Handles
(Switch Body listed on Bulletin 194L Control and Load Switches)