



a		b		c			
Installation Type		Load Size		Function/Circuit Diagram Ref. #			
Code	Description	Code	Description	Code	Function	Description	Circuit Diagram Ref. #
A	Base/DIN mounting	16	16 A	1753	OFF/ON	3-pole, 2-position (90°)	1753
E	Front/Door mounting	25	25 A	1756	OFF/ON	6-pole, 2-position (90°)	1756
		32	32 A	1783	OFF/ON	3-pole, 2-position (90° - inverted)	1783
		40	40 A	3753	Changeover	3-pole, 3-position (90°)	3753
		63	63 A				
		80	80 A				
		100	100 A				

Frequently Ordered★ OFF-ON 3-Pole Switch (includes operating shaft) (Handles listed on Bulletin 194E/194L Handles (for use with Bulletin 194E Switches))

Function Switching Angle	Contact Target Configuration X = Contact Closed O = Contact Open			Rated Current [A]	AC23A Rated Power [kW] at 690V AC 50 Hz	Hp @ 480V AC 60 Hz 3ΦPhase	OFF-ON 3-Pole Switch (includes operating shaft)	
	No. of Circuits	Handle Position					Base-Mounted	Front-Mounted
		OFF/0	ON/1				Cat. No.	Cat. No.
								
	1	O	X	16	7.5	7.5	194E-A16-1753	194E-E16-1753
	2	O	X	25	11	10	194E-A25-1753	194E-E25-1753
	3	O	X	32	15	15	194E-A32-1753	194E-E32-1753
				40	18.5	20	194E-A40-1753	194E-E40-1753
				63	22	25	194E-A63-1753	194E-E63-1753
				80	37	40	194E-A80-1753	194E-E80-1753
				100	45	50	194E-A100-1753	194E-E100-1753

Frequently Ordered★ OFF-ON 6-Pole Switch (includes operating shaft) (Handles listed on Bulletin 194E/194L Handles (for use with Bulletin 194E Switches))

Function Switching Angle	Contact Target Configuration X = Contact Closed O = Contact Open			Rated Current [A]	AC23A Rated Power [kW] at 690V AC 50 Hz	Hp @ 480V AC 60 Hz 3ØPhase	OFF-ON 6-Pole Switch (includes operating shaft)	
	No. of Circuits	Handle Position					Base-Mounted	Front-Mounted
		OFF/0	ON/1				Cat. No.	Cat. No.
								
	1	O	X	16	7.5	7.5	194E-A16-1756	194E-E16-1756
	2	O	X	25	11	10	194E-A25-1756	194E-E25-1756
	3	O	X					
	4	O	X	32	15	15	194E-A32-1756	194E-E32-1756
	5	O	X	40	18.5	20	194E-A40-1756	194E-E40-1756
	6	O	X	63	22	25	194E-A63-1756	194E-E63-1756
				80	37	40	194E-A80-1756	194E-E80-1756
				100	45	50	194E-A100-1756	194E-E100-1756

★ See Catalog No. Explanation for more load size and change-over switch options.

Bulletin 194E/194L Handles (for use with Bulletin 194E Switches)