






		1492-J6FB1...			1492-J6FB2...		
Dimensions are not intended to be used for manufacturing purposes. <b>Note:</b> Height dimension is measured from top of rail to top of terminal block.							
<b>Specifications</b>		Single-circuit fuse block with or without blown fuse indication			Single-circuit fuse block with or without blown fuse indication		
Certifications		UL	CSA	IEC	UL	CSA	IEC
Voltage Rating	J6FB1/J6FB2	600V AC/DC			500V AC/DC		
	J6FB124/J6FB224	10...36V AC/DC			10...36V AC/DC		
	J6FB148/J6FB248	30...70V AC/DC			30...70V AC/DC		
	J6FB1120/J6FB2120	60...150V AC/DC			60...150V AC/DC		
	J6FB1250/J6FB2250	100...250V AC/DC			100...250V AC/DC		
Maximum Current		10 A	16 A	6.3 A	10 A	10 A	6.3 A
Wire Range (Rated Cross Section)		#22...8 AWG	#20...8 AWG	6 mm <sup>2</sup>	#22...8 AWG	#20...8 AWG	6 mm <sup>2</sup>
Wire Strip Length		0.47 in. (12 mm)			0.47 in. (12 mm)		
Recommended Tightening Torque		10.6 lb•in (1.2 N•m)			14.2 lb•in (1.6 N•m)		
Density		25 pcs/ft (84 pcs/m)			38 pcs/ft (126 pcs/m)		
Housing Temperature Range		-58...+248 °F (-50...+120 °C)			-58...+248 °F (-50...+120 °C)		
Leakage Current		≤ 0.5 mA at Nominal Voltage			≤ 0.5 mA at Nominal Voltage		
Fuse Size (not supplied)		1/4 x 1-1/4 in.			5 x 20 mm		
<b>Terminal Blocks</b>		<b>Cat. No.</b>			<b>Pkg Qty.</b>		
Color:	Black No-indication	1492-J6FB1			30		
	Black w/LED	1492-J6FB124			25		
	Black w/LED	1492-J6FB148			25		
	Black w/LED	1492-J6FB1120			25		
	Black w/LED	1492-J6FB1250			25		
<b>Accessories</b>		<b>Cat. No.</b>			<b>Pkg Qty.</b>		
Mounting Rails:		199-DR1			10		
1 m Symmetrical DIN (Steel)		199-DR1			10		
1 m Symmetrical DIN (Aluminum)		1492-DR5			10		
1 m Hi-Rise Sym. DIN (Aluminum)		1492-DR6			2		
1 m Angled Hi-Rise Sym. DIN (Steel)		1492-DR7			2		
End Barrier		1492-EBJ3			50		
End Anchors and Retainers:		1492-EAJ35			100		
DIN Rail – Normal Duty		1492-EAJ35			100		
DIN Rail – Heavy Duty		1492-EAHJ35			50		
Jumpers 		1492-CJJFB1-2			50		
Center Jumper, 2-pole		1492-CJJFB1-2			50		
Center jumper, 10-pole		1492-CJJFB1-10			50		
Screws for center jumpers		1492-CJJ6FBMS			1		
Notching tool		1492-CJJ6FBTL			1		
Other Accessories:		1492-EBJ16			20		
Partition Plate		1492-EBJ16			20		
Marking Systems:		1492-M7X12			5		
Snap-In Marker Card		1492-M7X12			5		

 Center jumpers are shipped unassembled and require the screws and notching tool listed to assemble.

		1492-H...			1492-WFB4...		
Dimensions are not intended to be used for manufacturing purposes. <b>Note:</b> Height dimension is measured from top of rail to top of terminal block.							
<b>Specifications</b>		Single-circuit fusible terminal block with or without fuse indication.			Single-circuit fuse block with or without fuse indication.		
Certifications			CSA	IEC		CSA	IEC