

Spring-Clamp Connection Terminal Blocks



Multi-Circuit Feed-Through Blocks

1492-LD4

1492-LTF3

Dimensions are not intended to be used for manufacturing purposes.

Note: Height dimension is measured from top of rail to top of terminal block.

**Specifications**

Two-circuit feed-through terminal block

Three-circuit feed-through terminal block with multiple cross connection points

		CSA	IEC		CSA	IEC
Voltage Rating	600V AC/DC		800V AC/DC	300V AC/DC		500V AC/DC
Maximum Current	25 A	30 A	32 A	15 A		20 A
Wire Range (Rated Cross Section)	#26...10 AWG		4 mm ²	#26...12 AWG		2.5 mm ²
Wire Strip Length	0.39 in. (10 mm)			0.39 in. (10 mm)		
Density	49 pcs/ft (163 pcs/m)			59 pcs/ft (196 pcs/m)		
Housing Temperature Range	-58...+248 °F (-50...+120 °C)			-58...+248 °F (-50...+120 °C)		

Terminal Blocks

		Cat. No.	Pkg Qty.		Cat. No.	Pkg Qty.
Color	Grey	1492-LD4	20		1492-LTF3	25
	Red	1492-LD4-RE	20		—	—
	Blue	1492-LD4-B	20		—	—
	Black	1492-LD4-BL	20		—	—
	Green	1492-LD4-G	20		—	—
	Yellow	1492-LD4-Y	20		—	—
	Orange	1492-LD4-OR	20		—	—
	Brown	1492-LD4-BR	20		—	—
	White	1492-LD4-W	20		—	—

Accessories

		Cat. No.	Pkg Qty.		Cat. No.	Pkg Qty.
Mounting Rails						
1 m Symmetrical DIN (Steel)		199-DR1	10		199-DR1	10
1 m Symmetrical DIN (Aluminum)		1492-DR5	10		1492-DR5	10
1 m Hi-Rise Sym. DIN (Aluminum)		1492-DR6	2		1492-DR6	2
1 m Angled Hi-Rise Sym. DIN (Steel)		1492-DR7	2		1492-DR7	2
End Barriers	Grey	1492-EBLD4	20		1492-EBLTF3	20
	Blue	1492-EBLD4-B	20		—	—
	Yellow	1492-EBLD4-Y	20		—	—
End Anchors and Retainers						
Screwless End Retainer		1492-ERL35	20		1492-ERL35	20
DIN Rail — Normal Duty		1492-EAJ35	100		1492-EAJ35	100
DIN Rail — Heavy Duty		1492-EAHJ35	50		1492-EAHJ35	50
Jumpers						
Plug-in Center Jumper — 50-Pole		—	—		1492-CJK5-50	10
Plug-in Center Jumper — 10-Pole		1492-CJK6-10	20		1492-CJK5-10	20
Plug-in Center Jumper — 9-Pole		1492-CJK6-9	20		1492-CJK5-9	20
Plug-in Center Jumper — 8-Pole		1492-CJK6-8	20		1492-CJK5-8	20
Plug-in Center Jumper — 7-Pole		1492-CJK6-7	20		1492-CJK5-7	20
Plug-in Center Jumper — 6-Pole		1492-CJK6-6	20		1492-CJK5-6	20
Plug-in Center Jumper — 5-Pole		1492-CJK6-5	20		1492-CJK5-5	20
Plug-in Center Jumper — 4-Pole		1492-CJK6-4	60		1492-CJK5-4	60
Plug-in Center Jumper — 3-Pole		1492-CJK6-3	60		1492-CJK5-3	60
Plug-in Center Jumper — 2-Pole		1492-CJK6-2	60		1492-CJK5-2	60
Vertical Cross Connector*		—	—		1492-CJL5D	20
Other Accessories						
Reducing Sleeves 26...24 AWG (0.13...0.2 mm ²)		—	—		1492-PSLTF3-2	100
Reducing Sleeves 22...20 AWG (0.25...0.5 mm ²)		—	—		1492-PSLTF3-5	100
Test Plug		1492-TP23	20		—	—
Electrical Warning Plate		1492-EWPL6	20		—	—
Marking Systems						
Snap-In Marker Cards		1492-M6X10 (120/card)	5		1492-SM5X10 (144/card)	5
Snap-In Marker Cards		1492-M6X5 (200/card)	5		1492-M5X5 (200/card)	5

* Used to electrically connect 2 levels of 1492-LTF3

IEC Terminal Block Accessories

Jumpers

Side Jumpers

For Use With	Pkg Qty.	Cat. No.
1492-WM4, W4	50	1492-N42
1492-H4, H5, H6, H7	10	1492-N49
	10	* 1492-SJS
1492-W3, WR3	10	1492-SJ5-10
1492-JD3, JD3C, JD3F, JDG3, JD3DF, JD3DR, JD3SS, JDG3P	50	1492-SJ5A-10
1492-JD3, JD3C, JD3F, JDG3, JD3DF, JD3DR, JD3SS, JDG3P	50	1492-SJ5A-24
1492-JD3, JD3C, JD3F, JDG3, JD3DF, JD3DR, JD3SS, JDG3P	50	1492-SJ5B-24
1492-JD3, JD3C, JD3F, JDG3, JD3DF, JD3DR, JD3SS, JDG3P	50	1492-SJ5B-10
1492-WM4, W4, W4TW	10	⚡ 1492-SJ6-10
1492-JT3M	5	1492-SJ6A-50
1492-W10	10	1492-SJ8-10
1492-JD3FB, JDG3FB	50	1492-SJ8A-4
1492-JD3FB, JDG3FB	50	1492-SJ8A-3
1492-JD3FB, JDG3FB	50	1492-SJ8A-2
1492-LMP3, LMP3Q, LMJ3, LM3, LM3Q, LMP3E, LMP3QE	50	1492-SJLM5-2
1492-WMD1	10	‡ 1492-SJMD5-12
1492-WFB4, WFB424, WFB4250	10	1492-SJFB8-10
1492-WM3	10	1492-SJM5-10
1492-WTF3, WTS3, WTF3LP, WTS3LP, WTF3LN, WTS3LN	10	1492-SJT5-20-R
1492-WTF3, WTS3, WTF3LP, WTS3LP, WTF3LN, WTS3LN	10	1492-SJT5-20-B

Note: Side jumpers carry the same current rating as the terminal block used with it

* Side jumper insulating sleeve only for use with Cat. No. 1492-N49

⚡ Use jumper on single side of terminal block only

‡ Uninsulated

Two-Level Jumper

For Use With	Pkg Qty.	Cat. No.
1492-LTF3 (Connects Two Levels within a 1492-LTF3 Terminal Block)	20	1492-CJL5D

